

DSE8610

AUTO START LOAD SHARE MODULE

FEATURES



The DSE8610 is an easy to use multi-generator loadshare system, designed to synchronise up to 32 generators including electronic and non-electronic engines.

The DSE8610 monitors the generator and indicates operational status and fault conditions, automatically starting or stopping the engine on load demand or fault condition.

System alarms are annunciated on the LCD screen (multiple language options available), illuminated LED and audible sounder.

The event log will record 250 events to facilitate easy maintenance. An extensive number of fixed and flexible monitoring, metering and protection features are included as well as comprehensive communication and system expansion options.

Using the DSE PC Configuration Suite Software allows easy alteration of the operational sequences, timers and alarms. With all communication ports capable of being active at the same time, the DSE8610 is ideal for a wide variety of demanding load share applications.

KEY LOAD SHARE FEATURES:

- Peak lopping
- Sequential set start
- Manual voltage/frequency adjustment
- R.O.C.O.F. and vector shift
- Generator load demand
- Automatic hours run balancing
- Mains (Utility) de-coupling
- Mains (Utility) de-coupling test mode
- Dead bus sensing
- Bus failure detection
- Direct governor and AVR control
- Volts and frequency matching
- kW and kV Ar load sharing

ENVIRONMENTAL TESTING STANDARDS

ELECTRO MAGNETIC COMPATIBILITY

BS EN 61000-6-2
EMC Generic Immunity Standard for the Industrial Environment
BS EN 61000-6-4
EMC Generic Emission Standard for the Industrial Environment

ELECTRICAL SAFETY

BS EN 60950
Safety of Information Technology Equipment, including Electrical Business Equipment

TEMPERATURE

BS EN 60068
Ab/Ae Cold Test -30°C
BS EN 60068-2-2
Bb/Be Dry Heat +70°C

VIBRATION

BS EN 60068-2-6
Ten sweeps in each of three major axes
5Hz to 8Hz @ +/-7.5mm, 8Hz to 500Hz @ 2gn

HUMIDITY

BS EN 60068-2-30
Db Damp Heat Cyclic 20/55°C @ 95% RH
48 Hours
BS EN 60068-2-78
Cab Damp Heat Static 40°C @ 93% RH
48 Hours


SHOCK

BS EN 60068-2-27
Three shocks in each of three major axes
15gn in 11mS

DEGREES OF PROTECTION PROVIDED BY ENCLOSURES

BS EN 60529
IP65 - Front of module when installed into the control panel with the supplied sealing gasket.

COMPREHENSIVE FEATURE LIST TO SUIT A WIDE VARIETY OF LOAD SHARE APPLICATIONS



DSE8610

AUTO START LOAD SHARE MODULE

FEATURES



KEY FEATURES

- Comprehensive loadshare capabilities
- Configurable inputs (11)
- Configurable outputs (8)
- Voltage measurement
- Built-in governor and AVR control
- kW overload alarms
- Comprehensive electrical protection
- Magnetic pick-up
- Electronic engine capability
- RS232 & RS485 remote communications
- Modbus RTU
- PLC functionality
- Multi event exercise timer
- Back-lit LCD 4-line text display
- Multiple display languages
- Automatic start/Manual start
- Audible alarm
- Reduced file transfer time

- Fixed and flexible LED indicators
- Event log (250)
- Engine protection
- Fault condition notification to a designated PC
- Protected front panel programming
- PC configuration
- Fully configurable
- SMS alert messaging
- Compatible with DSE8700 Series

KEY BENEFITS

- RS232 & RS485 can be used at the same time
- DSENet connection for system expansion
- PLC functionality
- Auto voltage sensing
- Five step dummy load support
- Five step load shedding support
- High number of inputs and outputs

- Worldwide language support
- Configuration Suite PC software
- Direct USB connection to PC
- Ethernet monitoring
- USB host
- Data logging & trending

EXPANSION DEVICES

- DSE2131 Ratiometric Input Expansion Module
- DSE2133 RTD/Thermocouple Input Expansion Module
- DSE2152 Analogue Output Expansion Module
- DSE2548 LED Expansion Module
- DSE2130 Input Expansion Module
- DSE2157 Output Expansion Module
- DSE124 CAN/MSB Extender

RELATED MATERIALS

TITLE

DSE8610 Installation Instructions
 DSE8610 Operator Manual
 DSE8600 PC Configuration Suite Manual
 DSE8660 Date Sheet

PART NO'S

053-069
 057-115
 057-119
 055-086

SPECIFICATION

DC SUPPLY

CONTINUOUS VOLTAGE RATING
 8 V to 35 V continuous

CRANKING DROPOUTS

Able to survive 0 V for 50 mS, providing supply was at least 10 V before dropout and supply recovers to 5 V. This is achieved without the need for internal batteries

MAXIMUM OPERATING CURRENT

460 mA at 12 V, 245 mA at 24 V

MAXIMUM STANDBY CURRENT

375 mA at 12 V, 200 mA at 24 V

CHARGE FAIL/EXCITATION RANGE

0 V to 35 V

OUTPUTS

OUTPUT A (FUEL)

15 A DC at supply voltage

OUTPUT B (CRANK)

15 A DC at supply voltage

OUTPUTS C & D

8 A AC at 250 V AC (Volt free)

AUXILIARY OUTPUTS E,F,G

2 A DC at supply voltage

GENERATOR & BUS VOLTAGE RANGE

15 V to 333 V AC (L-N)

FREQUENCY RANGE

3.5 Hz to 75 Hz

MAGNETIC PICK-UP VOLTAGE RANGE

+/- 0.5 V to 70 V

FREQUENCY RANGE

10,000 Hz (max)

BUILT-IN GOVERNOR CONTROL

MINIMUM LOAD IMPEDANCE
 1000Ω
 Fully isolated

GAIN VOLTAGE

0 V to 10 V DC
 Fully isolated

OFFSET VOLTAGE

+/- 10 V DC
 Fully isolated

BUILT-IN AVR CONTROL

MINIMUM LOAD IMPEDANCE
 1000Ω
 Fully isolated

GAIN VOLTAGE

0 V to 10 V DC
 Fully isolated

OFFSET VOLTAGE

+/- 10 V DC
 Fully isolated

DIMENSIONS

OVERALL
 240 mm x 172 mm x 57 mm
 9.4" x 6.8" x 2.2"

PANEL CUTOUT

220 mm x 160 mm
 8.7" x 6.3"

MAXIMUM PANEL THICKNESS

8 mm
 0.3"

STORAGE TEMPERATURE RANGE

-40 °C to +85 °C

DEEP SEA ELECTRONICS PLC UK

Highfield House, Hunmanby Industrial Estate, Hunmanby YO14 0PH
TELEPHONE +44 (0) 1723 890099 **FACSIMILE** +44 (0) 1723 893303
EMAIL sales@deepseapl.com **WEBSITE** www.deepseapl.com

DEEP SEA ELECTRONICS INC USA

3230 Williams Avenue, Rockford, IL 61101-2668 USA
TELEPHONE +1 (815) 316 8706 **FACSIMILE** +1 (815) 316 8708
EMAIL sales@deepseausa.com **WEBSITE** www.deepseausa.com